

Mode: WT-F001-3Classic



3W Solar Panel



220V Charging Interface



特点和性能

- 可以太阳能供电，也可以市电充电；
- 体积小，机构简单，易于安装
- 高亮度 LED
- 自主运行时间长
- 多档位调节

Features and Benefits

- Solar Powered Directly and AC Charging
- Compact. Portable and durable
- High luminance LED
- Running long time after fully charged
- Multi file adjustment

应用

- 室内照明
- 走廊庭院照明
- 露营及业务作业
- 灾难救生照明

Application

- Indoor Lighting
- Corridor court Lighting
- Camping and field operation
- Lighting disaster lifesaving

Solar LED Lanterns WT-F001-3 Specification

Product Code	WT-F001-3
Number of LED Per Lantern	SMD2835 36PCS
Ingress Protection	IP20
AC Input	110-220V 50/60Hz
DC Input	DC Jack 6V
LED information:	
Lamp Brightness	260 lumens for high brightness 50lumens for low brightness
Lamp Power	4W
Lifetime of LED	LM80
Color Temperature	5500K-6500K
Battery Information:	
Battery Type	Sealed Maintenance Free (SMF) lead acid battery 4V.2.0AH
Battery Buck Up	4V 2.0AH
AC Charging Time	10-12Hrs
Solar Charging Time	14-15Hrs
Working Time	3-4Hrs with high brightness ≥20Hrs with low brightness
Packing Information(Lamp Only):	
Unit Dimension	123*123*173mm
Inner Packing Size	126*126*180
Outer Packing Size	650*270*380
Gross Weight Per Pcs	450g/Pcs
Solar Panel:	
Solar LED Panel Type	3W 6.0V .0.5A Polycrystalline Solar Panel
Solar Panel Dimensions	235*140*17 mm
Solar Panel connecting cable length	2M
Solar Panel characteristics	A stand at the back of solar panel to maintain 30 degrees facing to the Sun.

Solar LED Lanterns WT-F001-3 Specifization

Operation Information	1. Please read the instructions and fully charged before Use;
	2. Before plugging in an external battery or power supply, please make sure if the power supply is correct;
	3. During the use process, when the LED lamp brightness get dimmed and batteries become fully discharged state, in order to protect the battery, please stop using and charge it in time at this time. Shouldn't charge after the LED lamp is completely no light, because easily lead to excessive discharge battery failure extremely;
	4. Must use more than 8 hours every three months;
	5. Make the lamp off when not in use
	6. When the temperature is below 0 degrees or above 40 degrees, use and charging efficiency will be reduced;
	7. Do not go near water or rain;
Maintenance	1. solar panel surface clean
	2. The solar panel surface cannot be scratched and damaged.
Scrap products	1. In order to reduce pollution of the environment, please do not throw the battery, battery to a designated disposal agency or the designated bins.