

Mode: WT-F013 Economy



220V Charging Interface

## 特点和性能

- 可以太阳能供电，也可以市电充电；
- 体积小，机构简单，易于安装
- 高亮度 LED
- 自主运行时间长
- 多档位调节

## Features and Benefits

- Solar Powered Directly and AC Charging
- Compact. Portable and durable
- High luminance LED
- Running long time after fully charged
- Multi file adjustment

## 应用

- 室内照明
- 走廊庭院照明
- 露营及业务作业
- 灾难救生照明

## Application

- Indoor Lighting
- Corridor court Lighting
- Camping and field operation
- Lighting disaster lifesaving

## Solar LED Lanterns WT-F013 Specification

<b>Product Code</b>	WT-F013
<b>Number of LED Per Lantern</b>	SMD
<b>Ingress Protection</b>	IP20
<b>AC Input</b>	220V 50/60Hz
<b>Solar Charging Input</b>	DC Jack 9V
<b>Indicator</b>	Full Charging Indicator
<b>LED information:</b>	
<b>Lamp Brightness</b>	150lumens for high brightness 20 Lumens for high brightness
<b>Lamp Power</b>	6W
<b>Lifetime of LED</b>	LM-80
<b>Color Temperature</b>	5500-6500K
<b>Battery Information:</b>	
<b>Battery Type</b>	Sealed Maintenance Free (SMF) lead acid battery
<b>Battery Back Up</b>	4V 3.0AH
<b>AC Charging Time</b>	20-24Hrs
<b>Working Time</b>	3Hrs with high brightness; ≥30Hrs with low brightness;
<b>Packing Information(Lamp Only):</b>	
<b>Unit Dimension</b>	122*122*283
<b>Inner Packing Size</b>	125*125*283
<b>outer Packing Size</b>	640*390*303/ 15Pcs
<b>Gross Weight Per Box</b>	11.8Kg

## Solar LED Lanterns WT-F013 Specification

<b>Operation Information</b>	1. Please read the instructions and fully charged before Use;
	2. Before plugging in an external battery or power supply, please make sure if the power supply is correct;
	3. During the use process, when the LED lamp brightness get dimmed and batteries become fully discharged state, in order to protect the battery, please stop using and charge it in time at this time. Shouldn't charge after the LED lamp is completely no light, because easily lead to excessive discharge battery failure extremely;
	4. Must use more than 8 hours every three months;
	5. Make the lamp off when not in use
	6. When the temperature is below 0 degrees or above 40 degrees, use and charging efficiency will be reduced;
	7. Do not go near water or rain;
<b>Maintenance</b>	1. solar panel surface clean
	2. The solar panel surface cannot be scratched and damaged.
<b>Scrap products</b>	1. In order to reduce pollution of the environment, please do not throw the battery, battery to a designated disposal agency or the designated bins.