

Mode: WT-F002Economy



220V Charging Interface

特点和性能

- 可以太阳能供电，也可以市电充电；
- 体积小，机构简单，易于安装
- 高亮度 LED
- 自主运行时间长
- 多档位调节

Features and Benefits

- Solar Powered Directly and AC Charging
- Compact. Portable and durable
- High luminance LED
- Running long time after fully charged
- Multi file adjustment

应用

- 室内照明
- 走廊庭院照明
- 露营及业务作业
- 灾难救生照明

Application

- Indoor Lighting
- Corridor court Lighting
- Camping and field operation
- Lighting disaster lifesaving

Solar LED Lanterns WT-F002 Specification

Product Code	WT-F002
Number of LED Per Lantern	SMD 24PCS
Ingress Protection	IP20
AC Input	110-220V 50/60Hz
Solar Charging Input	DC Jack 9V
LED information:	
Lamp Brightness	350lumens for high brightness 20 Lumens for high brightness
Lamp Power	5W
Lifetime of LED	LM-80
Color Temperature	5500-6500K
Battery Information:	
Battery Type	Sealed Maintenance Free (SMF) lead acid battery
Battery Back Up	6V 4.5AH
AC Charging Time	20-24Hrs
Working Time	10-14Hrs with high brightness; 20Hrs with low brightness;
Packing Information(Lamp Only):	
Unit Dimension	110*115*200
Inner Packing Size	190*190*288
outer Packing Size	775*395*310
Gross Weight Per Box	11.8Kg

Solar LED Lanterns WT-F002 Specification

<http://www.westechlighting.com>

Copyright ©2016 WESTECH. All Rights Reserved.

Operation Information	1. Please read the instructions and fully charged before Use;
	2. Before plugging in an external battery or power supply, please make sure if the power supply is correct;
	3. During the use process, when the LED lamp brightness get dimmed and batteries become fully discharged state, in order to protect the battery, please stop using and charge it in time at this time. Shouldn't charge after the LED lamp is completely no light, because easily lead to excessive discharge battery failure extremely;
	4. Must use more than 8 hours every three months;
	5. Make the lamp off when not in use
	6. When the temperature is below 0 degrees or above 40 degrees, use and charging efficiency will be reduced;
	7. Do not go near water or rain;
Scrap products	1. In order to reduce pollution of the environment, please do not throw the battery, battery to a designated disposal agency or the designated bins.